



SE10000EC/TK1 10.0kVA

10.0kVA / 8.0KW ECE3/TIN 12 PORTABLE PETROL GENERATING SET (3000rpm)

OUTPUT:	10.0kVA / 8.0KW 50Hz, CTE 115 volt, single phase.
CONTROL BOX:	Alternator top mounted metal control box comprising, 1 x 32a & 1 x 16a , 1 x 63a 115v BS4343 socket outlets, and double pole MCB.
ENGINE:	Honda GX630 noise compliant and electric start twin cylinder air cooled petrol engine with "oil alert" low oil level shutdown, fitted with long run fuel tank and exhaust silencer.
ALTERNATOR:	NSM NUOVA SACCARDO MOTORI 2 Pole brushless maintenance free alternator, smooth waveform & voltage tolerance to suit electro fusion boxes & butt welding equipment.
FUEL TANK:	16.0 litre fuel tank giving 5.0 hours operation at 75% load
FRAME:	1" heavy duty tubular steel wrap-around frame, with tough powder coated finish
NOISE LEVEL:	75dB (A) @ 7 metres.
DIMENSIONS:	L860mm x W670mm x H750mm
WEIGHT:	125kg (dry).